



Tradicionalni punjač i tester za 12V olovne baterije.

PUNJAČ BATERIJA

- Za sve olovno-kiselinske pojačane baterije od 15 do 60 Ah.
- Indikator napunjenosti.
- Bakreni namot.
- Zaštićen od kratkog spoja i preopterećenja.

ISPITIVAČ

- Voltmetar do 15V.











Skladištenje kabela.

OPĆA ZAŠTITA



- Toplinska zaštita transformatora.
- Zaštićen od promjene polariteta zahvaljujući osiguraču od 10 A.
- Izolirane stezaljke.

CE - EN 60335-2-29

					Efficace/RMS	Moyen/Average (EN 60335)		IP			
50-60hz			MIN. Ah	MAX. Ah			fuse		cm	kg	
230 V	90 W	12 V	15-60 Ah		-	6 A	4 A	10 A	20	11.5 x 16 x 22	2.2

Made in China

www.gys.fr